

We bring Power to your Life

UAP3500 E

U Power Generation System



www.upower.com.tr
info@upower.com.tr
T. +90216 606 1380



Frequency (Hz) 50

Model UAP 3500 E

GASOLINE GENERATOR GROUP

- » Fuel gauge
- » Fuel gauge is on the fuel tank
- » OHV
- » Over Head Valve easy to maintenance
- » Oil level alarm
- » When the oil level is low that the engine will not start
- » AVR
- » AVR is a device often solid state, for controlling the output voltage of a generator
- » Circuit Protector
- » Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating
- » Voltmeter
- » It is a gauge for out put voltage of generator set
- » Choke System
- » When the cold weather, choke system aid to operate the engine
- » Dual Element air filter
- » Large capacity fuel tank 15-25 L

Generating Set

AC Rated Power	kW	2,50
	kW	3,00
Maximum Power	kW	2,80
	kW	3,50
AC Rated Current	AC Rated Current	10,00
Voltage	V	230
Frequency	Hz	50
Phase		1
Power Factor		0,80
Fuel Consumption	L/h	1,10
Noise Level	dB (A)	76,00

Engine

Speed	rpm	3000
Power	Hp	6,5
Cylinder No		1,0
Cylinder Bulk	mL	196
Fuel Type		Gasoline
Oil Capacity	L	0,6
Fuel Tank Capacity	L	15,0
Start Type		Electrical

Dimensions

Width (mm)	605	Height (mm)	490
Lenght (mm)	490	Dry Weight (kg)	50,0

Manufacturer reserves the right to make changes in the model, technical specifications, color, equipment, accessories and images without prior notice.