

# We bring Power to your Life



## UAP1200

U Power Generation System



[www.upower.com.tr](http://www.upower.com.tr)  
[info@upower.com.tr](mailto:info@upower.com.tr)  
T. +90216 606 1380



## ACTIVE POWER

Frequency (Hz) 50

Model UAP 1200

**GASOLINE GENERATOR GROUP**

» Fuel gauge

» Fuel gauge is on the fuel tank

» OHV

» Over Head Valve easy to maintenance

» Oil level alarm

» When the oil level is low that the engine will not start.

» AVR

» AVR is a device often solid state, for controlling the output voltage of a generator

» Circuit Protector

» Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating

» Voltmeter

» It is a gauge for out put voltage of generator set

» Choke System

» When the cold weather, choke system aid to operate the engine

» Dual Element air filter

### Generating Set

AC Rated Power	kW	0,90
Maximum Power	kW	1,00
AC Rated Current	AC Rated Current	3,40
Voltage	V	230
Frequency	Hz	50
Phase		1
Power Factor		1,00
Fuel Consumption	L/h	0,50
Noise Level	dB (A)	66,00

### Engine

Speed	rpm	3000
Fuel Type		Gasoline
Oil Capacity	L	0,4
Fuel Tank Capacity	L	7,0
Start Type		Rope

### Dimensions

Width	mm	355
Lenght	mm	465
Height	mm	385
Dry Weight	kg	26

Manufacturer reserves the right to make changes in the model, technical specifications, color, equipment, accessories and images without prior notice.