

We bring Power to your Life

UAP5500 E
U Power Generation System



www.upower.com.tr
info@upower.com.tr
T. +90216 606 1380



Frequency (Hz) 50 Model UAP 5500 E

GASOLINE GENERATOR GROUP

- » Fuel gauge
- » Fuel gauge is on the fuel tank
- » OHV
- » Over Head Valve easy to maintenance
- » Oil level alarm
- » Maintenance free battery
- » It is long life
- » Wheel kit
- » Easy Transportation
- » Voltmeter
- » It is a gauge for out put voltage of generator set
- » Choke System
- » Dual Element air filter
- » AVR
- » AVR is a device often solid state, for controlling the output voltage of a generator
- » Circuit Protector
- » Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating
- » When the cold weather, choke system aid to operate the engine
- » When the oil level is low that the engine will not start
- » Large capacity fuel tank 15-25 L

Generating Set

AC Rated Power	kW	4,00
	kW	5,00
Maximum Power	kW	4,50
	kW	5,50
AC Rated Current	AC Rated Current	17,30
Voltage	V	230
Frequency	Hz	50
Phase		1
Power Factor		0,80
Fuel Consumption	L/h	2,50
Run Time	Hour	10,00
Noise Level	dB (A)	73,00

Engine

Speed	rpm	3000
Power	Hp	11,0
Cylinder No		1,0
Cylinder Bulk	mL	337
Fuel Type		Gasoline
Oil Capacity	L	1,1
Fuel Tank Capacity	L	25,0
Start Type		Electrical

Dimensions

Width (mm)	540	Height (mm)	545
Lenght (mm)	680	Dry Weight (kg)	83,0